

# FLUSH MOUNT TOUCH SENSITIVE PUSH BUTTON

DINMTT is a request-to-exit switch, It will work independently (standalone) or can equally be connected via a controller to provide exit from a secured area (Push Button Input).

## **FEATURES**

- Feather light touch control
- Works in Pulse and Latch mode
- Ideal for a wide range of applications
- Front dual light indication
- Buzzer sound on every touch

# - SPECIFICATIONS -

- Input voltage: 12-24V DC; 15-24V AC

Current consumption: max.65mA
 Relay Output: 2A/24V AC/DC
 Indicators-LED: Normal - RED, Relay Operation - GREEN

- Operating Temperature: -20°C to 50°C


Humidity 5-80% non condensing

- Colours: Silver, Charcoal, and White

- Dimension (mm): 80L x 80W x 9H

- IP Rating: IP40

#### **DIMENSIONS** -






DINMTT EXIT

**DINMTT ARROW** 

#### **MOUNTING**



## **APPLICATIONS**

Light switch
Exit button (Access control)
Elevator button
Industrial panel

#### **COLOURS**







DINMTTC



All product specifications are subject to change without notice

